

ONYX¹⁵⁰

AC/DC Balancing LiPo Charger



THE BEST IN EASY, INEXPENSIVE LIPO CHARGING.

If you run 1-3S LiPo packs, there's only one charger you need: the Onyx 150. Built-in balancing ensures that each cell reaches maximum voltage, while other features make perfectly charged packs easy to achieve and afford. Compact and AC/DC compatible, the Onyx 150 can be used almost anywhere. All you need to do is plug it in, set the charge rate and hook up a pack. The Onyx 150 does the rest. It starts charging automatically — and stops the moment your pack has a full, deep charge. It's the last word in "set-and-forget" charging — and the best choice in budget-friendly, balanced charging.

DTXP4195 — AC/DC Balancing LiPo Charger

AC input: 110V 60Hz

DC input: 11-15V

Battery types: 1-3 LiPo cells (3.7-11.1V) only

Battery capacity range: 100-7500mAh

Fast charge current: 1.5A, 3.0A & 5.0A (50W max)

Input connections: Attached AC lead & detachable DC lead w/ alligator clips

Output connections: Attached lead w/Star Plug, Traxxas® adapter & universal radio jack for 1-3S LiPo Receiver packs

Balancing connector: Duratrax 3S with 2S adapter

Case Size: 5.3 x 5.0 x 1.9 in (133 x 127 x 48 mm)

Weight: 12.6 oz (356 g)

- Includes compact switching power supply for AC/DC charging convenience.
- Offers switch-settable charge rates, sound cues and a tri-color LED for status updates.
- Custom cc/cv charge profile ensures maximum voltage and prevents overcharging.
- Balances LiPo cells with +/- 5mV accuracy per cell.
- Includes 90-minute safety timer and a built-in cooling fan, plus reverse polarity and current overload protection.

For complete specifications, visit the Onyx 150 web page on duratrax.com.


duratrax.com

5 YEAR
LIMITED
WARRANTY
U.S.A. and Canada only